

Frequencies	Configuration	Beamwidth (@-3 dB)	RMS Power (W)	FOM (dB)	Q	Series Imped- ance (R-jX)
200 kHz-BClq Broadband	\bigcirc	9°	500 W	-16	2	60-j0(t)

SPECIFICATIONS

Weight: 1.5 kg

Acoustic Window: Urethane

Cable Type: C-33—Shielded twisted pair (2-20 AWG) with braided shield, black neoprene jacket, 6 mm diameter

Technical Data-200 kHz-BClg TVR in dB re 1µPa/Volt at 1 m RVR in dB re 1 Volt/µPa





Echogram

Directivity Pattern-200 kHz-BClq



Verti Horiz	 		-			Z/DIN	/	
		ľ	1					
							AN I	_
	-		1		-			_
					-			
			I	-	-			
			ľ		-			_

FOM

TECHNOLOGY CORPORATION



High-Frequency

Ultrasonic Transduce

Applications

River, harbor, and estuary survey

Features

- Broadband with low Q of 2
- Minimal sidelobes for concentrated energy on target providing excellent definition
- Internal transformer provides impedance match to echosounder and allows use of longer cable
- 500 W RMS, power rating is at 2% duty cycle
- Do not strike or use solvents (especially acetone) on the transducer face. Use water-base anti-fouling paint only. Do not cut transducer cable.
- Seamless, SEALCAST[™], urethane housing resists cuts and abrasion and has excellent, impact resistance

Options

Impedance to customer's specifications using matching transformer

Dimensions





©Airmar Technology Corporation

M194_rF 02/16/11

As Airmar constantly improves its products, all specifications are subject to change without As Airmar constantly improves its products, all specifications are subject to change without notice. All Airmar products are designed to provide high levels of accuracy and reliability, however they should only be used as aids to navigation and not as a replacement for traditional navigation aids and techniques. SEALCAST™ is a trademark of Airmar Technology Corporation. Other company or product names mentioned in this document may be trademarks or registered trademarks of their respective companies, which are not

may be trademarks or registered trademarks of their respective cor FAXff@755483376182 E-MAIL: szss20@163.com

www.airmar.com