

measure. analyze. innovate.

Low Level Force Sensor

M10x1, Axial Connector, -50 ... 50 N

Quartz force sensor with high sensitivity for measuring quasistatic and dynamic tensile and compressive forces in the range of less than 1 mN to 50 N. General applications. The sensor is mounted in a bore with a M10x1 thread and the force is introduced at its front end. The sensor has a hermetically sealed housing and is well suited for laboratory and industrial applications.

- 3 calibrated measuring ranges
- Dynamic measuring range 1 : 100 000
- Highly sensitive, for forces of 1 mN and over
- For tensile and compression forces
- Low sensitivity to transverse forces and temperature
- High rigidity

Description

The sensor possesses a highly sensitive, transversal quartz element, which is mounted without preload. Therefore the sensor is largely insensitive to thermal influences. The force is introduced through the cylindrical front end which is supported on the housing by a diaphragm of special design. The ceramic insulated connector is hermetically sealed.

Technical Data

Measuring range	Fz	Ν	-50 50
Overload	Fz	Ν	-75/150
Calibrated measuring ranges			
100 %	Fz	Ν	-50 50
10 %	Fz	Ν	-5 5
1 %	Fz	Ν	-0,5 0,5
Threshold	Fz	Ν	<0,5 · 10 ⁻³
Sensitivity	Fz	pC/N	≈–115
Linearity, all measuring ranges		%FSO	≤±1
Hysteresis, all measuring ranges		%FSO	≤0,5
Transverse force ¹⁾ , max.	F _{x,y}	Ν	10
Transverse force sensitivity	$F_{x,y}\toF_z$	N/N	≤±0,05
Bending moment, max.	M _{x.y}	N∙m	0,25
Sensitivity to bending moment	$M_{x,y} \to F_z$	N/N∙m	≤±3
Torque, max.	Mz	N∙m	0,15
Rigidity	Cz	N/µm	≈4

¹⁾ Force application in the plane of the cylindrical front end.

Туре 9207



Natural frequency	kHz	>10
Acceleration sensitivity		
axial	N/g	<0,03
radial	N/g	<3 · 10-3
Operating temperature range	°C	-50 150
Temperature coefficient of sensitivity		
–50 … 150 °C	%/°C	≈–0,02
Insulation resistance, at 20 °C	Ω	>1013
Capacitance	pF	≈26
Connector (ceramic insulator)	KIAG 10-32 neg.	
Degree of protection (with cable connected)	EN60529	IP65
Case material	DIN	1.4542
Weight	g	19
Tightening torque, max.		
M10x1	N∙m	10
M3	N∙m	0,2

Page 1/2

This information corresponds to the current state of knowledge. Kistler reserves the right to make technical changes. Liability for consequential damage resulting from the use of Kistler products is excluded.

©2005, Kistler Instrumente AG, PO Box, Eulachstr. 22, CH-8408 Winterthur Tel +41 52 224 11 11, Fax +41 52 224 14 14, info@kistler.com, www.kistler.com

measure. analyze. innovate.

Application Examples

- Measuring contact forces on keys, buttons, switches, relays etc.
- Measuring spring characteristics.
- Measuring extraction forces of plug-in contacts.
- Construction of highly sensitive miniature force plates, e.g. for measurements in wind tunnels.
- · Force measurements on automatic assembly units, robots, micro-manipulators, etc.

Mounting

Mounting in a bore with M10x1 thread and force introduction at the front end with M3 thread (see Fig. 1).



Fig. 1: Mounting with M10x1 thread, front sided force introduction

The force introducing cap (Fig. 2) is used for point force introduction. The coupling element Type 9405 (Fig. 3) is used to reduce transverse forces and bending moments acting on the sensor.



9207_000-130e-12.05



ø 6,3





Caution!

This force sensor is a very sensitive measuring instrument. Greatest care is compulsory when handling the sensor as no overload protection is provided.

Accessories Included Туре

- Force introducing cap 3.220.139
- Fork wrench SW 5,5 5.210.096

Optional Accessories Туре

٠	Coupling	element		9405
---	----------	---------	--	------

• Connecting cable KIAG 10-32 pos. - BNC pos. Length 1 m 1631C1 length 2 m 163102

Lungui z m	105102
Length 5 m	1631C5
Length 10 m	1631C10

(see also data sheet cables for force, torque and strain sensors 1631C_000-346)

Ordering Key	Туре
Low Level Force Sensor	9207
M10x1, Axial Connector, –50 50 N	

Page 2/2

This information corresponds to the current state of knowledge. Kistler reserves the right to make technical changes. Liability for consequential damage resulting from the use of Kistler products is excluded.

©2005, Kistler Instrumente AG, PO Box, Eulachstr. 22, CH-8408 Winterthur Tel +41 52 224 11 11, Fax +41 52 224 14 14, info@kistler.com, www.kistler.com